

FIRE ALARM CONTROL PANEL

A fire always has a devastating impact, whether at home or at work. The rapid detection of a fire situation is crucial to its combat and extinction, mainly to reduce the human and material risks.

The Fire Alarm Control Panel - FIREWALL - combines the best technology with the elegant design, with a simple and intuitive interface, for the prevention and detection of fires.

The FIREWALL complies with EN-54, offering high safety standards.



Main Characteristics

- Models of 2, 4, 8 and 16 zones, up to 32 detectors per zone.
- Smart and automatic zones.
- 'Day Mode' function allows to avoid false alarms.
- Powered through a unique battery of 12VDC / 7Ah.
- Auxiliary outputs per zone.
- Up to 2 programmable relays.
- Output supply of 24 VDC up to 500 mA.
- Siren alarm output up to 500 mA.

Advantages

- Certification EN54-2/-4 (CPR)
- Elegant design
- Simple and intuitive interface with access by code or key
- Flush and surface mount
- Low consumption
- Only one battery
- Benefit in insurances
- Sustainable product
- RoHS compliant
- After sale support fast and professional



Areas of application:



FIREWALL



Power supply	100 - 240 VAC, 50/60 Hz 45 VA
Battery	1 battery 12 VDC, 7 Ah (or 2 batteries 6 VDC, 12 Ah)
Standby current	60 mA
Maximum current	1 A
Fuse	Main supply - 4 A 24V - 1.6 A Fire Alarm - 500 mA
Fire Alarm Output	24 VDC, 500 mA
Relay contacts	250 VAC, 10 A
Zones	24 V < 65 mA Up to 32 conventional detectors with termination resistor in parallel of 3300 Ω, 1/4 W. [Callpoint with zener diodes in series 5V1, 1/4W]
Auxiliary Outputs	80 VDC, 500 mA (open-collector)
Dimension	Width: 255 mm Height: 360 mm Depth: 93 mm Hole for cables: 8 x Ø 20 mm

New Features



Related Products



Callpoint



Remote Indicator



Outdoor Siren Alarm



**FIRE
ALARM
PANEL**

NIBBLE®

Rua Júlio Dinis, 265, 1D
4785-330 Trofa - Portugal
41° 20' 14.01" -8° 33' 46.10"

(+351) 252 418 349

www.nibble.pt

info@nibble.pt